



All dimensions are in mm

**Documents**

Interface  
Handling instruction

Rosenberger internal standard  
HI\_003

Dieses Dokument ist urheberrechtlich geschützt • This document is protected by copyright • Rosenberger Hochfrequenztechnik GmbH & Co. KG

RF\_35/09 14/6.2

**Material and plating**

**Parts**

Housing  
Casting compound  
Magnets

**Material**

PBT-GF30 FR  
PU casting resin  
NdFeB

**Plating / Colour**

black, sim. RAL 9005  
Nickel

**Pins 1-4:**

Contact Pin

Brass

Gold, 0,15 µm

**Pins 5-6:**

Power Pin

Copper

Nickel, min. 3 µm

**Electrical data**

**Pins 1-4:**

Insulation resistance ≥ 100 MΩ  
Contact resistance ≤ 40 mΩ initial  
Working voltage 12 V  
Max. Current 3 A per pin

**Pins 5-6:**

Insulation resistance ≥ 100 MΩ  
Power current ≤ 10 A DC  
Contact resistance ≤ 7 mΩ  
Working voltage ≤ 60V DC

**Mechanical data**

Locking mechanism magnetic  
Mating cycles min. 2500  
Disengagement force min. 20N  
Weight 14 g

**Warning!**

**Customer is responsible for implementing adequate safety measures:**

**Power supply to Pins 5 & 6 must be deactivated unless they are completely plugged in.**

**Power to pins 5 & 6 must only be activated upon full insertion of signal pins 1 - 4.**

**Misuse may damage contact!**

**Environmental data**

Temperature range	-40°C to +65°C
Thermal shock	DIN IEC 60068-2-14 Test Na
Temperature and humidity	DIN EN 60068-2-30 (2)
Vibration resistance	3 axes, 6h, 10Hz-180Hz, 12.38m/s <sup>2</sup>
Mechanical Shock	DIN IEC 60068-2-27
High-Temp. Exposure	DIN IEC 60068-2-2
Dust and water resistance (Interface)	DIN-EN-60529 IP 65; unmated
Dust and water resistance	DIN-EN-60529 IP 64 / IP 67; mated
Glow-wire flammability test for end-products (GWT850°C; GWT750°C)	IEC 60695-2-11:2014
RoHS	compliant

**Suitable cables**

Cable type	
<b>Pins 1-4:</b>	
Wire Cross Section:	0.35 mm <sup>2</sup>
<b>Pins 5-6:</b>	
Wire Cross Section:	1.0 mm <sup>2</sup>

**Packing**

Standard	depends on wire length
	Connector is only available with cable

**Caution!**

**Magnets can impact the function of pace makers and implantable cardioverter-defibrillators (e.g. actuation of reed switch). Keep a minimum distance of 0,2m (20cm) between the magnetic connector and the implanted devices to prevent malfunction and danger to health.**

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
H. Kreitmaier	02.08.11	C. Biermann	27.05.21	600	21-1019	F. Huber	27.05.21

Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany <a href="http://www.rosenberger.de">www.rosenberger.de</a>	Tel. : +49 8684 18-0 Email : <a href="mailto:info@rosenberger.de">info@rosenberger.de</a>	Page 3 / 3
--	--	---------------